

NEUMANN BOUNDARY CONTROLLABILITY OF THE KORTEWEG-DE VRIES EQUATION ON A BOUNDED DOMAIN

MIGUEL CAICEDO, ROBERTO A. CAPISTRANO-FILHO, AND BING-YU ZHANG

ABSTRACT. In this paper we study boundary controllability of the Korteweg-de Vries (KdV) equation posed on a finite domain $(0, L)$ with the Neumann boundary conditions:

$$(0.1) \quad \begin{cases} u_t + u_x + uu_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = 0, \quad u_x(L, t) = h(t), \quad u_{xx}(L, t) = 0 & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L). \end{cases}$$

We show that the associated linearized system

$$(0.2) \quad \begin{cases} u_t + (1 + \beta)u_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = 0, \quad u_x(L, t) = h(t), \quad u_{xx}(L, t) = 0 & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L), \end{cases}$$

is exactly controllable if and only if $\beta \neq -1$ and the length L of the spatial domain $(0, L)$ does not belong to set

$$\mathcal{R}_\beta := \left\{ \frac{2\pi}{\sqrt{3(1+\beta)}} \sqrt{k^2 + kl + l^2} : k, l \in \mathbb{N}^* \right\} \cup \left\{ \frac{k\pi}{\sqrt{1+\beta}} : k \in \mathbb{N}^* \right\}.$$

Then the nonlinear system (0.1) is shown to be locally exactly controllable around a constant steady state β if the associated linear system is exactly controllable.

1. INTRODUCTION

In this paper we study a class of distributed parameter control system described by the Korteweg-de Vries (KdV) equation posed on a bounded interval $(0, L)$ with the Neumann boundary conditions:

$$(1.1) \quad \begin{cases} u_t + u_x + uu_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = 0, \quad u_x(L, t) = h(t), \quad u_{xx}(L, t) = 0 & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L), \end{cases}$$

where the boundary value function $h = h(t)$ will be considered as a control input. We are mainly concerned with its exact control problem:

Given $T > 0$ and $u_0, u_T \in L^2(0, L)$, can one find an appropriate control input h such that the corresponding solution u of (1.1) satisfies

$$u(x, 0) = u_0(x), \quad u(x, T) = u_T(x)?$$

The study of control and stabilization of the KdV equation begun with the works of Russell [19], Zhang [26], Russell and Zhang [20, 21] in which they studied internal control of the KdV equation posed on a finite domain $(0, L)$ with periodic boundary conditions. Aided by then newly discovered Bourgain smoothing properties [2, 3] they showed that the internal control system is locally exactly controllable and exponentially stabilizable¹. Since then, control and stabilization of the KdV equation have been intensively studied (see [4, 5, 6, 8, 9, 10, 16, 17, 18, 25] and references

2010 *Mathematics Subject Classification.* Primary: 35Q53, Secondary: 37K10, 93B05, 93D15.

Key words and phrases. Korteweg-de Vries equation, exact boundary controllability, Neumann boundary conditions, Dirichlet boundary conditions, critical set.

¹The system has been shown recently to be globally exponentially stabilizable and large time exactly controllable by Laurent, Rosier and Zhang [15].

therein). In particular, Rosier [16] studied boundary control of the KdV equation posed on the finite domain $(0, L)$ with the Dirichlet boundary conditions:

$$(1.2) \quad \begin{cases} u_t + u_x + uu_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u(0, t) = 0, \ u(L, t) = 0, \ u_x(L, t) = g(t) & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L), \end{cases}$$

where boundary value function $g(t)$ is considered as a control input. Rosier considered first the associated linear system

$$(1.3) \quad \begin{cases} u_t + u_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u(0, t) = 0, \ u(L, t) = 0, \ u_x(L, t) = g(t) & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L) \end{cases}$$

and discovered the so-called *critical length* phenomena; whether the system (1.3) is exactly controllable depends on the length L of the spatial domain $(0, L)$.

Theorem A (Rosier [16]) *The linear system (1.3) is exactly controllable in the space $L^2(0, L)$ if and only if the length L of the spatial domain $(0, L)$ does not belong to the set*

$$(1.4) \quad \mathcal{N} := \left\{ \frac{2\pi}{\sqrt{3}} \sqrt{k^2 + kl + l^2} : k, l \in \mathbb{N}^* \right\}.$$

The controllability result of the linear system was then extended to the nonlinear system when $L \notin \mathcal{N}$.

Theorem B (Rosier [16]): *Let $T > 0$ be given and assume $L \notin \mathcal{N}$. There exists $\delta > 0$ such for any $u_0, u_T \in L^2(0, L)$ with*

$$\|u_0\|_{L^2(0, L)} + \|u_T\|_{L^2(0, L)} \leq \delta,$$

one can find a control input $g \in L^2(0, T)$ such that the nonlinear system (1.2) admits a unique solution

$$u \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$$

satisfying

$$u(x, 0) = u_0(x), \quad u(x, T) = u_T(x).$$

In the case of $L \in \mathcal{N}$, Rosier proved in [16] that the associated linear system (1.3) is not controllable; there exists a finite-dimensional subspace of $L^2(0, L)$, denoted by $\mathcal{M} = \mathcal{M}(L)$, which is unreachable from 0 for the linear system. More precisely, for every nonzero state $\psi \in \mathcal{M}$, $g \in L^2(0, T)$ and $u \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$ satisfying (1.3) and $u(\cdot, 0) = 0$, one has $u(\cdot, T) \neq \psi$. A spatial domain $(0, L)$ is called *critical* for the system (1.3) if its domain length $L \in \mathcal{N}$.

When the spacial domain $(0, L)$ is critical, one usually would not expect the corresponding nonlinear system (1.2) to be exactly controllable as the linear system (1.3) is not. It thus came as a surprise when Coron and Crépeau showed in [8] that the nonlinear system (1.2) is still locally exactly controllable even though its spatial domain is critical with its length $L = 2k\pi$ and $k \in \mathbb{N}^*$ satisfying

$$\nexists(m, n) \in \mathbb{N}^* \times \mathbb{N}^* \text{ with } m^2 + mn + n^2 = 3k^2 \text{ and } m \neq n.$$

For those values of L , the unreachable space $\mathcal{M}$ of the associated linear system is an one-dimensional linear space generated by the function $1 - \cos(x)$. As for the other types of the critical domains, the nonlinear system (1.2) was shown later by Cerpa [4], and Cerpa and Crépeau in [6] to be locally, large time exactly controllable.

Theorem C (Crépeau and Cerpa [4, 6]): *Let $L \in \mathcal{N}$ be given. There exists a $T_L > 0$ such that for any $T > T_L$ there exists $\delta > 0$ such for any $u_0, u_T \in L^2(0, L)$ with*

$$\|u_0\|_{L^2(0, L)} + \|u_T\|_{L^2(0, L)} \leq \delta,$$

there exists $g \in L^2(0, T)$ such that the system (1.2) admits a unique solution

$$u \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$$

satisfying

$$u(x, 0) = u_0(x), \quad u(x, T) = u_T(x).$$

In this paper, we will investigate the boundary control system (1.1) of the KdV equation posed on the finite domain $(0, L)$ with the Neumann boundary conditions to see if it possesses similar control properties as that possessed by the boundary control system (1.2). First we will study the following linearized system associated to (1.1),

$$(1.5) \quad \begin{cases} u_t + (1 + \beta)u_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = 0, \quad u_x(L, t) = h(t), \quad u_{xx}(L, t) = 0 & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L), \end{cases}$$

where β a given real constant. For any $\beta \neq -1$, we define

$$(1.6) \quad \mathcal{R}_\beta := \left\{ \frac{2\pi}{\sqrt{3(1+\beta)}} \sqrt{k^2 + kl + l^2} : k, l \in \mathbb{N}^* \right\} \cup \left\{ \frac{k\pi}{\sqrt{\beta+1}} : k \in \mathbb{N}^* \right\}.$$

The following theorem is one of the main results in this paper.

Theorem 1.1.

- (i) If $\beta \neq -1$, the linear system (1.5) is exactly controllable in the space $L^2(0, L)$ if and only if the length L of the spatial domain $(0, L)$ does not belong to the set $\mathcal{R}_\beta$.
- (ii) If $\beta = -1$, then the system (1.5) is not exact controllable in the space $L^2(0, L)$ for any $L > 0$.

The next theorem addressing controllability of the nonlinear system (1.1) is our another main result of the paper.

Theorem 1.2. Let $T > 0$, $\beta \neq -1$ and $L \notin \mathcal{R}_\beta$ be given. There exists a $\delta > 0$ such that for any $u_0, u_T \in L^2(0, L)$ with

$$\|u_0 - \beta\|_{L^2(0, L)} + \|u_T - \beta\|_{L^2(0, L)} \leq \delta,$$

one can find a control input $h \in L^2(0, T)$ such that the system (1.1) admits unique solution

$$u \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$$

satisfying

$$u(x, 0) = u_0(x), \quad u(x, T) = u_T(x).$$

The following remarks are now in order:

Remark 1.3. In the case of $\beta = 0$, $\mathcal{N}$ is a proper subset of $\mathcal{R}_0$. The linear system (1.5) has more critical length domains than that of the linear system (1.3). In the case of $\beta = -1$, every $L > 0$ is critical for the system (1.5). By contrast, if we remove the term u_x from the equation in (1.3), every $L > 0$ is not critical for the system (1.3).

Remark 1.4. Every constant β is a steady state solution of the system (1.1), but is not for the system (1.2). The system (1.2) is only known to be locally exact controllable around the origin. By contrast, the system (1.1) is locally exactly controllable around any constant steady state β as long as $L \notin \mathcal{R}_\beta$.

Theorem 1.1 will be proved using the same approach that Rosier used to establish Theorem A. However, one will encounter some difficulties that demand special attention. The adjoint system of the linear system (1.5) is given by

$$(1.7) \quad \begin{cases} \psi_t + (1 + \beta)\psi_x + \psi_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ (1 + \beta)\psi(0, t) + \psi_{xx}(0, t) = 0 & \text{in } (0, T), \\ (1 + \beta)\psi(L, t) + \psi_{xx}(L, t) = 0 & \text{in } (0, T), \\ \psi_x(0, t) = 0 & \text{in } (0, T), \\ \psi(x, T) = \psi_T(x) & \text{in } (0, L). \end{cases}$$

It is well known that the exact controllability of system (1.5) is equivalent to the following observability inequality for the adjoint system (1.7):

$$(1.8) \quad \|\psi_T\|_{L^2(0, L)} \leq C \|\psi_x(L, \cdot)\|_{L^2(0, T)}.$$

However, the usual multiplier method and compactness arguments as those used in dealing with the system (1.7) only lead to

$$(1.9) \quad \|\psi_T\|_{L^2(0, L)}^2 \leq C_1 \|\psi_x(L, \cdot)\|_{L^2(0, T)}^2 + C_2 \|\psi(L, \cdot)\|_{L^2(0, T)}^2.$$

One has to find a way to remove the extra term present in (1.9). For this, a technical lemma presented below, which reveals some hidden regularities (or sharp trace regularities) for solutions of the adjoint system (1.7), is needed.

Lemma 1.5. (*Hidden regularities*) *For any $\psi_T \in L^2(0, L)$, the solution*

$$\psi \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$$

of IBVP (1.7) possesses the following sharp trace properties

$$(1.10) \quad \sup_{x \in (0, L)} \|\partial_x^r \psi(x, \cdot)\|_{H^{\frac{1-r}{3}}(0, T)} \leq C_r \|\psi_0\|_{L^2(0, L)}$$

for $r = 0, 1, 2$.

The sharp Kato smoothing properties of solutions of the Cauchy problem of the KdV equation posed on the whole line $\mathbb{R}$ due to Kenig, Ponce and Vega [12] will play an important role in the proof of Lemma 1.5.

Following the work of Rosier [16], the boundary control system of the KdV equation posed on the finite interval $(0, L)$ with various control inputs has been intensively studied (cf. [9, 10, 11] and see [5, 18] for more complete reviews)

$$(1.11) \quad \begin{cases} u_t + u_x + uu_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u(0, t) = g_1(t), \quad u(L, t) = g_2(t), \quad u_x(L, t) = g_3(t) & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L). \end{cases}$$

The system (1.11) has been found to have an interesting property: it behaves like a parabolic system if control only applied on the left end of the spatial domain $(0, L)$ ($g_2 = g_3 \equiv 0$): the system is only null controllable; but if control is allowed to apply on the right end of the spatial domain $(0, L)$, the system behaves like a hyperbolic system which is exactly controllable. Moreover, the critical length phenomena occurs only in the case that just one control is applied to the right end of the spatial domain $(0, L)$.

In this paper we will also show that the boundary control systems of the KdV equation posed on $(0, L)$ with Neumann boundary conditions,

$$(1.12) \quad \begin{cases} u_t + u_x + uu_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = h_1(t), \quad u_x(L, t) = h_2(t), \quad u_{xx}(L, t) = h_3(t) & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L), \end{cases}$$

possess similar properties.

Theorem 1.6. *Let $T > 0$ and $L > 0$ be given. There exists $\delta > 0$ such that for any $u_0, u_T \in L^2(0, L)$ with*

$$\|u_0\|_{L^2(0,L)} + \|u_T\|_{L^2(0,L)} \leq \delta,$$

one can find h_1, h_2 , and h_3 satisfy one of the conditions below

- (i) $h_1 \in H^{-\frac{1}{3}}(0, T)$ and $h_2 \in L^2(0, T)$, $h_3 = 0$;
- (ii) $h_2 \in L^2(0, T)$, $h_3 \in H^{-\frac{1}{3}}(0, T)$ and $h_1 = 0$;
- (iii) $h_1, h_3 \in H^{-\frac{1}{3}}(0, T)$, $h_2 = 0$,

such that the system (1.12) admits unique solution

$$u \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$$

satisfying

$$u(x, 0) = u_0(x), \quad u(x, T) = u_T(x).$$

If all three boundary control inputs are used, then the system (1.12) has much stronger controllability; it is locally exactly controllable around any smooth solution of the KdV equation in the space $H^s(0, L)$ for any $s \geq 0$ and is large time globally exactly controllable in the space $H^s(0, L)$ for any $s \geq 0$.

Theorem 1.7. *Let $T > 0$, $s \geq 0$ and $L > 0$ be given. Assume that $y \in C^\infty(\mathbb{R}, H^\infty(\mathbb{R}))$ satisfies*

$$y_t + y_x + yy_x + y_{xxx} = 0 \quad (x, t) \in \mathbb{R} \times \mathbb{R}.$$

Then, there exists $\delta > 0$ such that for any $y_0, y_T \in H^s(0, L)$ with

$$\|u_0 - y(\cdot, 0)\|_{H^s(0,L)} + \|u_T - y(\cdot, T)\|_{H^s(0,L)} \leq \delta,$$

one can find

$$h_1 \in H^{\frac{s-1}{3}}(0, T), \quad h_2 \in H^{\frac{s}{3}}(0, T), \quad h_3 \in H^{\frac{s-1}{3}}(0, T)$$

such that system (1.12) admits a unique solution

$$u \in C([0, T]; H^s(0, L)) \cap L^2(0, T; H^{s+1}(0, L))$$

satisfying

$$u(x, 0) = u_0(x), \quad u(x, T) = u_T(x).$$

Theorem 1.8. *Let $L > 0$ and $\gamma > 0$ be given. There exists a $T > 0$ such that for any $u_0, u_T \in L^2(0, L)$ satisfying*

$$\|u_0\|_{L^2(0,L)} + \|u_T\|_{L^2(0,L)} \leq \gamma,$$

one can find

$$h_1 \in H^{-\frac{1}{3}}(0, T), \quad h_2 \in L^2(0, T), \quad h_3 \in H^{-\frac{1}{3}}(0, T)$$

such that system (1.12) admits a unique solution

$$u \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$$

satisfying

$$u(x, 0) = u_0(x), \quad u(x, T) = u_T(x).$$

Finally, if we consider the system with only control acting on the left end of the spatial domain $(0, L)$,

$$(1.13) \quad \begin{cases} u_t + u_x + u_{xxx} + uu_x = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = h_1(t), \quad u_x(L, t) = 0, \quad u_{xx}(L, t) = 0 & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L), \end{cases}$$

we have the following null controllability result.

Theorem 1.9 (Null Controllability). *Let $T > 0$ be fixed. For $\bar{u}_0 \in L^2(0, L)$, let*

$$\bar{u} \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$$

be the solution of the following system

$$(1.14) \quad \begin{cases} \bar{u}_t + \bar{u}_x + \bar{u}_{xxx} + \bar{u}\bar{u}_x = 0 & \text{in } (0, L) \times (0, T), \\ \bar{u}_{xx}(0, t) = 0, \bar{u}_x(L, t) = 0, \bar{u}_{xx}(L, t) = 0 & \text{in } (0, T), \\ \bar{u}(x, 0) = \bar{u}_0(x) & \text{in } (0, L). \end{cases}$$

Then, there exists $\delta > 0$ such that for any $u_0 \in L^2(0, L)$ satisfying

$$\|u_0 - \bar{u}_0\|_{L^2(0, L)} < \delta,$$

there exists $h_1(t) \in L^2(0, T)$ such that the solution $u(x, t)$ of the system (1.13) belongs to the space

$$C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$$

and satisfies

$$u(x, T) = \bar{u}(x, T) \quad \text{in } (0, L).$$

The paper is organized as follows.

— In Section 2, we study the non-homogeneous boundary value problem of the KdV equation on the finite interval $(0, L)$,

$$(1.15) \quad \begin{cases} u_t + u_x + uu_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = h_1(t), u_x(L, t) = h_2(t), u_{xx}(L, t) = h_3(t) & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L), \end{cases}$$

for its well-posedness in the space $L^2(0, L)$. We will show that the system (1.15) is locally well-posed in the space $L^2(0, L)$: for any $u_0 \in L^2(0, L)$,

$$h_1 \in H^{-\frac{1}{3}}(\mathbb{R}^+), h_2 \in L^2(\mathbb{R}^+), \text{ and } h_3 \in H^{-\frac{1}{3}}(\mathbb{R}^+),$$

there exists a $T > 0$ such that (1.15) admits a unique solution

$$u \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L)).$$

Various linear estimates including hidden regularities will be presented for solutions of the linear system associated to (1.15), which will play important roles in studying controllability of the system.

— In Section 3, the boundary control system (1.1) will be investigated for its controllability. We investigate first the linearized system (1.5) and its corresponding adjoint system (1.7) for their controllability and observability. In particular, the hidden regularities for solutions of the adjoint system (1.7) will be presented and then be used to prove Theorem 1.1 and Theorem 1.2.

— The sketch of proofs of Theorem 1.6 and Theorem 1.9 will be presented in Section 4 together with the proofs of Theorem 1.7 and Theorem 1.8.

We end our introduction with a few more comments. Having shown the nonlinear system (1.1) is locally exactly controllable (Theorem 1.2) if the length of the spatial domain is not critical, one naturally would like to show the system (1.1) is still locally exactly controllable when the length of its spatial domain is critical as in the case of system (1.2) (see Theorem C). We believe that the same approach developed in [4, 7, 8] to prove Theorem C for the system (1.2) can be adapted to obtain similar results for system (1.1). However, the Neumann boundary conditions present some extra difficulties. In particular, the adjoint linear system associated to (1.1) is different from the adjoint linear system associated to (1.2). The unobservable solutions of the adjoint system associated to (1.1) are not the solutions of the forward linear system associated to (1.1). When using the power series expansion method proposed in [7], there are more terms appeared that demand special handling. We plan to continue to study system (1.1) with the critical length for its controllability and present our results in the forthcoming paper.

2. WELL-POSEDNESS

In this section, we will show the initial-boundary value problem

$$(2.1) \quad \begin{cases} u_t + u_x + uu_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = h_1(t), \quad u_x(L, t) = h_2(t), \quad u_{xx}(L, t) = h_3(t) & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L), \end{cases}$$

is locally well-posed in the space $L^2(0, L)$ with $u_0(x) \in L^2(0, L)$ and

$$h_1, h_3 \in H^{-\frac{1}{3}}(0, T), \quad h_2 \in L^2(0, T).$$

We begin by considering the following linear non-homogeneous boundary value problem,

$$(2.2) \quad \begin{cases} w_t + w_{xxx} = 0, \quad w(x, 0) = 0 & x \in (0, L), t > 0, \\ w_{xx}(0, t) = h_1(t), \quad w_x(L, t) = h_2(t), \quad w_{xx}(L, t) = h_3(t) & t > 0. \end{cases}$$

First, we derive an explicit solution formula for its solution. Applying the Laplace transform with respect to t , (2.2) is converted to

$$(2.3) \quad \begin{cases} s\hat{w} + \hat{w}_{xxx} = 0, \\ \hat{w}_{xx}(0, s) = \hat{h}_1(s), \quad \hat{w}_x(L, s) = \hat{h}_2(s), \quad \hat{w}_{xx}(L, s) = \hat{h}_3(s), \end{cases}$$

where

$$\hat{w}(x, s) = \int_0^{+\infty} e^{-st} w(x, t) dt$$

and

$$\hat{h}_j(s) = \int_0^{+\infty} e^{-st} h_j(t) dt, \quad j = 1, 2, 3.$$

The solution $\hat{w}(x, s)$ can be written in the form

$$\hat{w}(x, s) = \sum_{j=1}^3 c_j(s) e^{\lambda_j(s)x},$$

where $\lambda_j(s)$, $j = 1, 2, 3$ are the solutions of the characteristic equation

$$s + \lambda^3 = 0$$

and $c_j(s)$, $j = 1, 2, 3$, solve the linear system

$$(2.4) \quad \underbrace{\begin{pmatrix} \lambda_1^2 & \lambda_2^2 & \lambda_3^2 \\ \lambda_1 e^{\lambda_1 L} & \lambda_2 e^{\lambda_2 L} & \lambda_3 e^{\lambda_3 L} \\ \lambda_1^2 e^{\lambda_1 L} & \lambda_2^2 e^{\lambda_2 L} & \lambda_3^2 e^{\lambda_3 L} \end{pmatrix}}_A \underbrace{\begin{pmatrix} c_1 \\ c_2 \\ c_3 \end{pmatrix}}_{\vec{h}} = \underbrace{\begin{pmatrix} \hat{h}_1 \\ \hat{h}_2 \\ \hat{h}_3 \end{pmatrix}}_{\vec{h}}.$$

By Cramer's rule,

$$c_j = \frac{\Delta_j(s)}{\Delta(s)}, \quad j = 1, 2, 3,$$

with Δ the determinant of A and Δ_j the determinant of the matrix A with the j th-column replaced by $\vec{h}$. The solution $w(x, t)$ for (2.2) can be written in the form

$$(2.5) \quad w(x, t) = \sum_{m=1}^3 w_m(x, t),$$

where $w_m(x, t)$ solves (2.2) with $h_j \equiv 0$ when $j \neq m$, $j, m = 1, 2, 3$. Using the inverse Laplace transform yields

$$w(x, t) = \frac{1}{2\pi i} \int_{r-i\infty}^{r+i\infty} e^{st} \hat{w}(x, s) ds = \sum_{j=1}^3 \frac{1}{2\pi i} \int_{r-i\infty}^{r+i\infty} \frac{\Delta_j(s)}{\Delta(s)} e^{\lambda_j(s)x} ds,$$

for $r > 0$. Combining this with (2.5) we can write the values of w_m as follows for $m = 1, 2, 3$,

$$w_m(x, t) = \sum_{j=1}^3 \frac{1}{2\pi i} \int_{r-i\infty}^{r+i\infty} \frac{\Delta_{j,m}(s)}{\Delta(s)} e^{\lambda_j(s)x} \hat{h}_m(s) ds \equiv [W_{m,j}(t)h_m](x).$$

In the last two formulas, the right-hand side are continuous with respect to r for $r \geq 0$. As the left-hand sides do not depend on r , we can take $r = 0$ in these formulas. Moreover,

$$w_{j,m}(x, t) = w_{j,m}^+(x, t) + w_{j,m}^-(x, t)$$

where

$$w_{j,m}^+(x, t) = \frac{1}{2\pi i} \int_0^{+i\infty} e^{st} \frac{\Delta_{j,m}(s)}{\Delta(s)} \hat{h}_m(s) e^{\lambda_j(s)x} ds$$

and

$$w_{j,m}^-(x, t) = \frac{1}{2\pi i} \int_{-i\infty}^0 e^{st} \frac{\Delta_{j,m}(s)}{\Delta(s)} \hat{h}_m(s) e^{\lambda_j(s)x} ds,$$

for $j, m = 1, 2, 3$. Here $\Delta_{j,m}(s)$ is obtained from $\Delta_j(s)$ by letting $\hat{h}_m(s) = 1$ and $\hat{h}_k(s) = 0$ for $k \neq m$, $k, m = 1, 2, 3$. Making the substitution $s = i\rho^3$ with $\rho \geq 0$ in the characteristic equation

$$s + \lambda^3 = 0.$$

The three roots are given in terms of ρ by

$$(2.6) \quad \lambda_1(\rho) = i\rho, \quad \lambda_2(\rho) = -i\rho \left(\frac{1+i\sqrt{3}}{2} \right), \quad \lambda_3(\rho) = -i\rho \left(\frac{1-i\sqrt{3}}{2} \right),$$

thus $w_{j,m}^+$ has the following form

$$w_{j,m}^+(x, t) = \frac{1}{2\pi i} \int_0^{+\infty} e^{i\rho^3 t} \frac{\Delta_{j,m}^+(\rho)}{\Delta^+(\rho)} \hat{h}_m^+(\rho) e^{\lambda_j^+(\rho)x} 3i\rho^2 d\rho$$

and

$$w_{j,m}^-(x, t) = \overline{w_{j,m}^+(x, t)},$$

where $\hat{h}_m^+(\rho) = \hat{h}_m(i\rho^3)$, $\Delta^+(\rho) = \Delta(i\rho^3)$, $\Delta_{j,m}^+(\rho) = \Delta_{j,m}(i\rho^3)$ and $\lambda_j^+(\rho) = \lambda_j(i\rho^3)$.

Then the solution of the IBVP (2.2) has the following representation.

Lemma 2.1. *Given $\vec{h} = (h_1, h_2, h_3)$, the solution w of the IBVP (2.2) can be written in the form*

$$w(x, t) = [W_{bdr}\vec{h}](x, t) := \sum_{j,m=1}^3 [W_{j,m}h_m](x, t).$$

Let $\vec{h} := (h_1, h_2, h_3) \in \mathcal{H}_T$ with

$$\mathcal{H}_T = H^{-\frac{1}{3}}(0, T) \times L^2(0, T) \times H^{-\frac{1}{3}}(0, T)$$

and

$$\mathcal{Z}_T := C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L)).$$

The following lemma holds, for solution of the system (2.2).

Proposition 2.2. *Let $T > 0$ be given. There exists a constant $C > 0$ such that for any $\vec{h} \in \mathcal{H}_T$ the system (2.2) admits a unique solution $w \in \mathcal{Z}_T$. Moreover, there exists a constant $C > 0$ such that*

$$\|w\|_{\mathcal{Z}_T} + \sum_{j=0}^2 \|\partial_x^j w\|_{L^\infty(0, L; H^{-\frac{1-j}{3}}(0, T))} \leq C \|\vec{h}\|_{\mathcal{H}_T}.$$

Proof. As we stated above, the solution w can be written as

$$w(x, t) = w_1(x, t) + w_2(x, t) + w_3(x, t).$$

We just prove Proposition 2.2 for w_1 . The proof for w_2 and w_3 are similar. Some straightforward calculations show that the asymptotic behavior of the ratios $\frac{\Delta_{j,m}^+(\rho)}{\Delta^+(\rho)}$ as $\rho \rightarrow +\infty$ are:

$\frac{\Delta_{1,1}^+(\rho)}{\Delta^+(\rho)} \sim \rho^{-2} e^{-\frac{\sqrt{3}}{2}\rho L}$	$\frac{\Delta_{2,1}^+(\rho)}{\Delta^+(\rho)} \sim \rho^{-2} e^{-\frac{\sqrt{3}}{2}\rho L}$	$\frac{\Delta_{3,1}^+(\rho)}{\Delta^+(\rho)} \sim \rho^{-2} e^{-\frac{\sqrt{3}}{2}\rho L}$
$\frac{\Delta_{1,2}^+(\rho)}{\Delta^+(\rho)} \sim \rho^{-1}$	$\frac{\Delta_{2,2}^+(\rho)}{\Delta^+(\rho)} \sim \rho^{-1}$	$\frac{\Delta_{3,2}^+(\rho)}{\Delta^+(\rho)} \sim \rho^{-1}$
$\frac{\Delta_{1,3}^+(\rho)}{\Delta^+(\rho)} \sim \rho^{-2}$	$\frac{\Delta_{2,3}^+(\rho)}{\Delta^+(\rho)} \sim \rho^{-2} e^{-\frac{\sqrt{3}}{2}\rho L}$	$\frac{\Delta_{3,3}^+(\rho)}{\Delta^+(\rho)} \sim \rho^{-2}$

Since

$$w_1(x, t) = \frac{3}{\pi} \sum_{j=1}^3 \int_0^{+\infty} e^{i\rho^3 t} e^{\lambda_j^+(\rho)x} \frac{\Delta_{j,1}^+(\rho)}{\Delta^+(\rho)} \hat{h}_1^+(\rho) \rho^2 d\rho,$$

we have

$$\begin{aligned} \sup_{t \in (0, T)} \|w_1(\cdot, t)\|_{L^2(0, L)}^2 &\leq C \int_0^\infty \mu^{-2/3} |\hat{h}_1^+(i\mu)|^2 d\mu \\ &\leq C \|h_1\|_{H^{-\frac{1}{3}}(\mathbb{R}^+)}^2 \\ &\leq C \|\vec{h}\|_{\mathcal{H}_T}^2. \end{aligned}$$

Furthermore, for $l = 0, 1, 2$, let us to consider $\theta(\mu)$ the real solution of $\mu = \rho^3$, $\rho \geq 0$, thus

$$\begin{aligned} \partial_x^l w_1(x, t) &= \frac{3}{\pi} \sum_{j=1}^3 \int_0^{+\infty} \left(\lambda_j^+(\rho)\right)^l e^{i\rho^3 t} e^{\lambda_j^+(\rho)x} \frac{\Delta_{j,1}^+(\rho)}{\Delta^+(\rho)} \hat{h}_1^+(\rho) \rho^2 d\rho \\ &= \frac{3}{\pi} \sum_{j=1}^3 \int_0^{+\infty} \left(\lambda_j^+(\theta(\mu))\right)^l e^{i\rho^3 t} e^{\lambda_j^+(\theta(\mu))x} \frac{\Delta_{j,1}^+(\theta(\mu))}{\Delta^+(\theta(\mu))} \hat{h}_1^+(i\mu) d\mu. \end{aligned}$$

Applying Plancherel theorem, in time t , yields that, for all $x \in (0, L)$

$$\begin{aligned} \|\partial_x^l w_1(x, \cdot)\|_{H^{\frac{1-l}{3}}(0, T)}^2 &\leq C \sum_{j=1}^3 \int_0^{+\infty} \mu^{\frac{2(1-l)}{3}} \left| \left(\lambda_j^+(\theta(\mu))\right)^{\rho+1} e^{\lambda_j^+(\theta(\mu))x} \frac{\Delta_{j,1}^+(\theta(\mu))}{\Delta^+(\theta(\mu))} \hat{h}_1^+(i\mu) \right|^2 d\mu \\ &\leq C \int_0^{+\infty} \mu^{-\frac{2}{3}} \left| \hat{h}_1(i\mu) \right|^2 d\mu \\ &\leq C \|h_1\|_{H^{-\frac{1}{3}}(0, T)}^2 \\ &\leq C \|\vec{h}\|_{\mathcal{H}_T}^2, \end{aligned}$$

for $l = 0, 1, 2$. Consequently

$$\sup_{x \in (0, L)} \|\partial_x^l w_1(x, \cdot)\|_{H^{\frac{1-l}{3}}(0, T)} \leq C \|\vec{h}\|_{\mathcal{H}_T}, \quad l = 0, 1, 2$$

which ends the proof of Proposition 2.2 for w_1 . □

Next we turn to consider the following initial boundary-value problem:

$$(2.7) \quad \begin{cases} v_t + v_{xxx} = f & x \in (0, L), t > 0, \\ v_{xx}(0, t) = 0, \quad v_x(L, t) = 0, \quad v_{xx}(L, t) = 0 & t > 0, \\ v(x, 0) = \phi(x) & x \in (0, L). \end{cases}$$

By semigroup theory, for any $\phi \in L^2(0, L)$ and $f \in L^1(0, T; L^2(0, L))$, it possess a unique mild solution $u \in C([0, T]; L^2(0, L))$ which can be written as

$$u(x, t) = W_0(t)\phi + \int_0^t W_0(t - \tau)f(\tau)d\tau.$$

Here $\{W_0(t)\}_{t \geq 0}$ is the C_0 -semigroup in the space $L^2(0, L)$ generated by linear operator

$$Ag = -g''$$

with domain

$$\mathcal{D}(A) = \{g \in H^3(0, L) : g''(0) = g'(L) = g''(L) = 0\}.$$

In order to show that the solution u of (2.7) also possesses the Kato smoothing property

$$u \in L^2(0, T; H^1(0, L))$$

and hidden regularity (sharp Kato smoothing property),

$$\partial_x^k u \in L_x^\infty(0, L; H^{\frac{1-k}{3}}(0, T)), \quad k = 0, 1, 2,$$

we rewrite u in terms of boundary integral operator $W_{bdr}(t)$ and the solution of the following initial value problem (IVP) of the linear KdV equation posed on the whole line $\mathbb{R}$,

$$(2.8) \quad \begin{cases} v_t + v_{xxx} = g(x, t) & x \in \mathbb{R}, \quad t \in \mathbb{R}^+, \\ v(x, 0) = \psi(x). \end{cases}$$

Recall that the solution $v(x, t)$ can be written as

$$v(x, t) = W_{\mathbb{R}}(t)\psi + \int_0^t W_{\mathbb{R}}(t - \tau)g(\tau)d\tau,$$

where $\{W_{\mathbb{R}}(t)\}_{t \in \mathbb{R}}$ is the C_0 group in the space $L^2(0, L)$ generated by the operator $Kg = -g'''$ with domain $\mathcal{D}(K) = H^3(\mathbb{R})$. The following results are well-known for solutions of (2.8) (see e.g. [12]).

Proposition 2.3. *For any $\psi \in L^2(\mathbb{R})$ and $g \in L^1(\mathbb{R}; L^2(\mathbb{R}))$, (2.8) admits a unique mild solution $v \in C(\mathbb{R}; L^2(\mathbb{R}))$ satisfying*

$$\|v(\cdot, t)\|_{L^2(\mathbb{R})} = \|\psi\|_{L^2(\mathbb{R})} \quad \text{for any } t \in \mathbb{R}.$$

Moreover, the the solution v possesses the local Kato smoothing property $v \in L^2(\mathbb{R}; H^1(-L, L))$ for any $L > 0$ with

$$\|v\|_{L^2(\mathbb{R}; H^1(-L, L))} \leq C_L (\|\psi\|_{L^2(\mathbb{R})} + \|g\|_{L^1(\mathbb{R}; L^2(\mathbb{R}))})$$

and the sharp Kato smoothing properties $\partial_x^k v \in L_x^\infty(\mathbb{R}; H_t^{(k-1)/3}(\mathbb{R}))$ with

$$\|\partial_x^k v\|_{L_x^\infty(\mathbb{R}; H^{(k-1)/3}(\mathbb{R}))} \leq C_k (\|\psi\|_{L^2(\mathbb{R})} + \|g\|_{L^1(\mathbb{R}; L^2(\mathbb{R}))})$$

for $k = 0, 1, 2$.

For $\phi \in L^2(0, L)$ and $f \in L^1(0, T; L^2(0, L))$, let

$$\tilde{\phi}(x) = \begin{cases} \phi(x) & \text{if } x \in (0, L), \\ 0 & \text{if } x \notin (0, L) \end{cases}$$

and

$$\tilde{f}(x, t) = \begin{cases} f(x, t) & \text{if } x \in (0, L) \times (0, T), \\ 0 & \text{if } x \notin (0, L) \times (0, T). \end{cases}$$

We have $\tilde{\phi} \in L^2(\mathbb{R})$, $\tilde{f} \in L^1(\mathbb{R}; L^2(\mathbb{R}))$ and

$$\|\tilde{\phi}\|_{L^2(\mathbb{R})} = \|\phi\|_{L^2(0, L)}, \quad \|\tilde{f}\|_{L^1(\mathbb{R}; L^2(\mathbb{R}))} = \|f\|_{L^1(0, T; L^2(0, L))}.$$

Let

$$v(x, t) = W_{\mathbb{R}}(t)\tilde{\phi} + \int_0^t W_{\mathbb{R}}(t - \tau)\tilde{f}(\tau)d\tau$$

and

$$q_1(t) = v_{xx}(0, t), \quad q_2(t) = v_x(L, t), \quad q_3(t) = v_{xx}(L, t), \quad \vec{q}(t) = (q_1(t), q_2(t), q_3(t)).$$

Then $v(x, t)$ solves (2.8) with ψ and g replaced by $\tilde{\phi}$ and $\tilde{f}$, respectively, and

$$u(x, t) = W_{\mathbb{R}}(t)\tilde{\phi} + \int_0^t W_{\mathbb{R}}(t - \tau)\tilde{f}(\tau)d\tau - W_{bdr}(t)\vec{q}$$

solves the IBVP (2.7). The following proposition then follows from Propositions 2.2 and 2.3.

Proposition 2.4. *Let $T > 0$ be given. For any $\phi \in L^2(0, L)$ and $f \in L^1(0, T; L^2(0, L))$, the IBVP (2.7) admits a unique mild solution $v \in C(\mathbb{R}; L^2(0, L))$ satisfying*

$$\|v(\cdot, t)\|_{L^2(0, L)} \leq C\|\psi\|_{L^2(0, L)} \quad \text{for any } t \in \mathbb{R}.$$

Moreover, the solution v possesses the local Kato smoothing property $v \in L^2(0, T; H^1(0, L))$ with

$$\|v\|_{L^2(0, T; H^1(0, L))} \leq C(\|\phi\|_{L^2(0, L)} + \|f\|_{L^1(0, T; L^2(0, L))})$$

and the sharp Kato smoothing properties $\partial_x^k v \in L_x^\infty(0, L; H^{(k-1)/3}(0, T))$ with

$$\|\partial_x^k v\|_{L_x^\infty(0, L; H^{(k-1)/3}(0, T))} \leq C_k(\|\phi\|_{L^2(0, L)} + \|f\|_{L^1(0, T; L^2(0, L))})$$

for $k = 0, 1, 2$.

Combining Proposition 2.3 and Proposition 2.4 together leads the result for the following IBVP:

$$(2.9) \quad \begin{cases} v_t + v_{xxx} = f & \text{in } (0, L) \times (0, T), \\ v_{xx}(0, t) = h_1, \quad v_x(L, t) = h_2, \quad v_{xx}(L, t) = h_3 & \text{in } (0, T), \\ v(x, 0) = v_0(x) & \text{in } (0, L). \end{cases}$$

Proposition 2.5. *Let $T > 0$ be given, for any $v_0 \in L^2(0, L)$, $f \in L^1(0, T; L^2(0, L))$ and*

$$\vec{h} := (h_1, h_2, h_3) \in \mathcal{H}_T = H^{-\frac{1}{3}}(0, T) \times L^2(0, T) \times H^{-\frac{1}{3}}(0, T),$$

the IBVP (2.9) admits a unique solution

$$v \in \mathcal{Z}_T := C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$$

with

$$\partial_x^k v \in L_x^\infty(0, L; H^{\frac{1-k}{3}}(0, T)) \quad \text{for } k = 0, 1, 2.$$

Moreover, there exists $C > 0$ such that

$$\|v\|_{\mathcal{Z}_T} + \sum_{k=0}^2 \|v\|_{L_x^\infty(0, L; H^{\frac{1-k}{3}}(0, T))} \leq C \left(\|v_0\|_{L^2(0, L)} + \|\vec{h}\|_{\mathcal{H}_T} + \|f\|_{L^1(0, T; L^2(0, L))} \right).$$

Next proposition states similar hidden (or sharp trace) regularities for the linear system

$$(2.10) \quad \begin{cases} y_t + y_x + y_{xxx} = f & x \in (0, L), t > 0 \\ y(0, t) = g_1(t), \quad y_x(L, t) = g_2(t), \quad y_{xx}(L, t) = g_3(t) & t > 0, \\ y(x, 0) = y_0(x) & x \in (0, L), \end{cases}$$

associated to (1.2).

Proposition 2.6. *Let $T > 0$ be given, for any $y_0 \in L^2(0, L)$, $f \in L^1(0, T; L^2(0, L))$ and*

$$\vec{g} := (g_1, g_2, g_3) \in \mathcal{G}_T = H^{\frac{1}{3}}(0, T) \times L^2(0, T) \times H^{-\frac{1}{3}}(0, T),$$

the IBVP (2.10) admits a unique solution $y \in \mathcal{Z}_T$. Moreover, there exists $C > 0$ such that

$$\|y\|_{\mathcal{Z}_T} \leq C(\|y_0\|_{L^2(0, L)} + \|\vec{g}\|_{\mathcal{G}_T} + \|f\|_{L^1(0, T; L^2(0, L))}).$$

In addition, the solution y possesses the following sharp trace estimates

$$(2.11) \quad \sup_{x \in (0, L)} \|\partial_x^r y(x, \cdot)\|_{H^{\frac{1-r}{3}}(0, T)} \leq C_r(\|y_0\|_{L^2(0, L)} + \|\vec{g}\|_{\mathcal{G}_T} + \|f\|_{L^1(0, T; L^2(0, L))}),$$

for $r = 0, 1, 2$.

The proof of Proposition 2.6 can be found in [1, 14].

Remark 2.7. *Systems (2.9) and (2.10) are equivalent in the following sense:*

Given $\{u_0, f, h_1, h_2, h_3\}$ one can find $\{y_0, f, g_1, g_2, g_3\}$ such that the corresponding solution u of (2.9) is exactly the same as the corresponding y for the system (2.10) and vice versa.

In fact, for given $u_0 \in L^2(0, L)$, $f \in L^1(0, T; L^2(0, L))$ and $\vec{h} \in \mathcal{H}_T$, system (2.9) admits a unique solution $u \in \mathcal{Z}_T$. Let $y_0 = u_0$ and set

$$g_1(t) = h_1(t), \quad g_3(t) = h_2(t), \quad g_2(t) = h_3(t).$$

Then, according to Proposition 2.4, we have $\vec{g} \in \mathcal{G}_T$. Due to the uniqueness of IBVP (2.10), with the selection $\{y_0, f, g_1, g_2, g_3\}$, the corresponding solution $y \in \mathcal{Z}_T$ of (2.10) must be equal to u since u also solves (2.10) with the given auxiliary data $\{y_0, f, g_1, g_2, g_3\}$. On the other hand, for any given $y_0 \in L^2(0, L)$, $f \in L^1(0, T; L^2(0, L))$ and $\vec{g} \in \mathcal{G}_T$, let $y \in \mathcal{Z}_T$ be the corresponding solution of the system (2.10). From (2.11), we have $y_{xx}(0, \cdot)$ and $y_{xx}(L, \cdot) \in H^{-\frac{1}{3}}(0, T)$. Thus, if set $u_0 = y_0$ and

$$h_1(t) = u_{xx}(0, t), \quad h_2(t) = g_3(t), \quad h_3(t) = u_{xx}(L, t),$$

then $\vec{h} \in \mathcal{H}_T$ and the corresponding solution $u \in \mathcal{Z}_T$ of (2.9) must be equal to y which also solves (2.9) with the auxiliary data $(u_0, f, \vec{h})$.

Finally, we are at the stage to prove the well-posedness of the of the following nonlinear system,

$$(2.12) \quad \begin{cases} u_t + u_x + uu_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = h_1(t), \quad u_x(L, t) = h_2(t), \quad u_{xx}(L, t) = h_3(t) & \text{in } (0, T), \\ u(x, 0) = u_0(x) := \phi(x) & \text{in } (0, L). \end{cases}$$

For given $T > 0$, define

$$X_T := L^2(0, L) \times H^{-\frac{1}{3}}(0, T) \times L^2(0, T) \times H^{-\frac{1}{3}}(0, T)$$

and

$$\mathcal{Z}_T := C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L)).$$

Theorem 2.8. *Let $T > 0$ and $r > 0$ be given. There exists a $T^* \in (0, T]$ such that for any $(\phi, \vec{h}) \in X_T$ with*

$$\|(\phi, \vec{h})\|_{X_T} \leq r,$$

the IBVP (2.12) admits a unique solution

$$u \in \mathcal{Z}_{T^*}.$$

In addition, the solution u possesses the hidden regularities

$$\partial_x^k u \in L_x^\infty(0, L; H^{\frac{1-k}{3}}(0, T^*)), \quad k = 0, 1, 2$$

and, moreover, the corresponding solution map is Lipschitz continuous.

Proof. Since the proof is similar to that presented in [1, 13], we will omit it. □

3. BOUNDARY CONTROLLABILITY

In this section, we study exact boundary controllability of the system

$$(3.1) \quad \begin{cases} u_t + u_x + uu_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = 0, \quad u_x(L, t) = h(t), \quad u_{xx}(L, t) = 0 & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L), \end{cases}$$

around a constant steady state $u \equiv c$. As it is easy to see by letting $u = v + c$, it is equivalent to study the exact boundary controllability of the following system

$$(3.2) \quad \begin{cases} v_t + (c+1)v_x + vv_x + v_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ v_{xx}(0, t) = 0, \quad v_x(L, t) = h(t), \quad v_{xx}(L, t) = 0 & \text{in } (0, T), \\ v(x, 0) = v_0(x) & \text{in } (0, L), \end{cases}$$

around the origin 0 instead. We have the following exact controllability results for the system (3.2).

Theorem 3.1. *Let $T > 0$, $c + 1 \neq 0$ and*

$$(3.3) \quad L \notin \mathcal{R}_c := \left\{ \frac{2\pi}{\sqrt{3(c+1)}} \sqrt{k^2 + kl + l^2} : k, l \in \mathbb{N}^* \right\} \cup \left\{ \frac{k\pi}{\sqrt{c+1}} : k \in \mathbb{N}^* \right\}$$

be given. Then there exists a $\delta > 0$ such that for any $v_0, v_T \in L^2(0, L)$ with

$$\|v_0\|_{L^2(0,L)} + \|v_T\|_{L^2(0,L)} \leq \delta,$$

one can find $h \in L^2(0, T)$ such that the system (3.2) admits unique solution

$$v \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$$

satisfying

$$v(x, 0) = v_0(x), \quad v(x, T) = v_T(x) \quad \text{in } (0, L).$$

To prove the Theorem 3.1, we first consider the linear system associated to (3.2)

$$(3.4) \quad \begin{cases} v_t + (c+1)v_x + v_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ v_{xx}(0, t) = 0, \quad v_x(L, t) = h(t), \quad v_{xx}(L, t) = 0 & \text{in } (0, T), \\ v(x, 0) = v_0(x) & \text{in } (0, L) \end{cases}$$

and its adjoint system

$$(3.5) \quad \begin{cases} \psi_t + (c+1)\psi_x + \psi_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ (c+1)\psi(0, t) + \psi_{xx}(0, t) = 0 & \text{in } (0, T), \\ (c+1)\psi(L, t) + \psi_{xx}(L, t) = 0 & \text{in } (0, T), \\ \psi_x(0, t) = 0 & \text{in } (0, T), \\ \psi(x, T) = \psi_T(x) & \text{in } (0, L). \end{cases}$$

Note that by transformation $x' = L - x$ and $t' = T - t$, the system (3.5) is equivalent of the following forward system

$$(3.6) \quad \begin{cases} \varphi_t + (c+1)\varphi_x + \varphi_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ (c+1)\varphi(0, t) + \varphi_{xx}(0, t) = 0 & \text{in } (0, T), \\ (c+1)\varphi(L, t) + \varphi_{xx}(L, t) = 0 & \text{in } (0, T), \\ \varphi_x(L, t) = 0 & \text{in } (0, T), \\ \varphi(x, 0) = \varphi_0(x) & \text{in } (0, L). \end{cases}$$

Proposition 3.2. *For any $\varphi_0 \in L^2(0, L)$, the system (3.6) admits a unique solution $\varphi \in \mathcal{Z}_T$ which, moreover, possesses the following hidden regularities*

$$(3.7) \quad \sup_{x \in (0, L)} \|\partial_x^r \varphi(x, \cdot)\|_{H^{\frac{1-r}{3}}(0, T)} \leq C_r \|\varphi_0\|_{L^2(0, L)},$$

for $r = 0, 1, 2$.

Remark 3.3. *Equivalently, for any $\psi_T \in L^2(0, L)$, the system (3.5) admits a unique solution $\psi \in \mathcal{Z}_T$ which, moreover, possesses the hidden regularities*

$$(3.8) \quad \sup_{x \in (0, L)} \|\partial_x^r \psi(x, \cdot)\|_{H^{\frac{1-r}{3}}(0, T)} \leq C_r \|\psi_T\|_{L^2(0, L)},$$

for $r = 0, 1, 2$.

Proof of Proposition 3.2. Let us consider the set

$$\mathcal{X}_T := \{u \in \mathcal{Z}_T : \partial_x^r u \in L_x^\infty(0, L; H^{\frac{1-r}{3}}(0, T)), r = 0, 1, 2\}$$

which is a Banach space equipped with the norm

$$\|u\|_{\mathcal{X}_T} := \|u\|_{\mathcal{Z}_T} + \sum_{r=0}^2 \|\partial_x^r u\|_{L_x^\infty(0, L; H^{\frac{1-r}{3}}(0, T))}.$$

According to Proposition 2.5, for any $v \in \mathcal{X}_\beta$ where $0 < \beta \leq T$ and any $\varphi_0 \in L^2(0, L)$, the system

$$(3.9) \quad \begin{cases} w_t + w_{xxx} = -(c+1)v_x & \text{in } (0, L) \times (0, T), \\ w_{xx}(0, t) = -(c+1)v(0, t) & \text{in } (0, T), \\ w_{xx}(L, t) = -(c+1)v(L, t) & \text{in } (0, T), \\ w_x(L, t) = 0 & \text{in } (0, T), \\ w(x, 0) = \varphi_0(x) & \text{in } (0, L), \end{cases}$$

admits a unique solution $w \in \mathcal{X}_\beta$ and, moreover,

$$\|w\|_{\mathcal{X}_\beta} \leq C \left(\|\psi_0\|_{L^2(0, L)} + \|v(0, \cdot)\|_{H^{-\frac{1}{3}}(0, T)} + \|v(L, \cdot)\|_{H^{-\frac{1}{3}}(0, T)} + \|v_x\|_{L^1(0, \beta; L^2(0, L))} \right),$$

where the constant $C > 0$ depends only on T . As we have,

$$\|v_x\|_{L^1(0, \beta; L^2(0, L))} \leq C\beta^{1/2}\|v\|_{\mathcal{X}_\beta},$$

$$\|v(0, \cdot)\|_{H^{-\frac{1}{3}}(0, \beta)} \leq \|v(0, \cdot)\|_{L^2(0, \beta)} \leq \beta^{2/3}\|v(0, \cdot)\|_{L^6(0, \beta)} \leq C\beta^{2/3}\|v(0, \cdot)\|_{H^{\frac{1}{3}}(0, \beta)} \leq C\beta^{2/3}\|v\|_{\mathcal{X}_\beta}$$

and

$$\|v(L, \cdot)\|_{H^{-\frac{1}{3}}(0, \beta)} \leq \|v(L, \cdot)\|_{L^2(0, \beta)} \leq \beta^{2/3}\|v(L, \cdot)\|_{L^6(0, \beta)} \leq C\beta^{2/3}\|v(L, \cdot)\|_{H^{\frac{1}{3}}(0, \beta)} \leq C\beta^{2/3}\|v\|_{\mathcal{X}_\beta},$$

the system (3.9) defines a map as follows

$$\begin{aligned} \Gamma : \mathcal{X}_\beta &\longrightarrow \mathcal{X}_\beta \\ v &\mapsto \Gamma(v) = w, \end{aligned}$$

for any $v \in \mathcal{X}_T$ and $\beta \in (0, \max\{1, T\}]$. Here $w \in \mathcal{X}_\beta$ is the corresponding solution of (3.9) and

$$\|\Gamma(v)\|_{\mathcal{X}_\beta} \leq C_1\|\psi_0\|_{L^2(0, L)} + C_2\beta^{1/2}\|v\|_{\mathcal{X}_\beta},$$

where C_1 and C_2 are two positive constants depending only on T . Choosing $r > 0$ and $\beta \in (0, \max\{1, T\}]$ such that

$$r = 2C_1\|\psi_0\|_{L^2(0, L)}$$

and

$$2C_2\beta^{1/2} \leq \frac{1}{2},$$

then, for any

$$v \in \mathcal{B}_{\beta, r} = \{v \in \mathcal{X}_\beta : \|v\|_{\mathcal{X}_\beta} \leq r\},$$

we have

$$\|\Gamma(v)\|_{\mathcal{X}_\beta} \leq r.$$

Moreover, for any $v_1, v_2 \in \mathcal{B}_{\beta, r}$, we get

$$\|\Gamma(v_1) - \Gamma(v_2)\|_{\mathcal{X}_\beta} \leq 2C_2\beta^{1/2}\|v_1 - v_2\|_{\mathcal{X}_\beta} \leq \frac{1}{2}\|v_1 - v_2\|_{\mathcal{X}_\beta}.$$

Therefore, the map Γ is a contraction mapping on $\mathcal{B}_{\beta, r}$. Its fixed point $w = \Gamma(v) \in \mathcal{X}_\beta$ is the desired solution for $t \in (0, \beta)$. As the chosen β is independent of φ_0 , the standard continuation extension argument yields that the solution w belongs to $\mathcal{X}_\beta$. The proof is complete. $\square$

The system (3.6) possesses an elementary estimate as described below.

Proposition 3.4. *Any solution φ of the adjoint system (3.6) with initial data $\varphi_0 \in L^2(0, L)$ satisfies*

$$(3.10) \quad \|\varphi_0\|_{L^2(0, L)}^2 \leq \frac{1}{T}\|\varphi\|_{L^2((0, L) \times (0, T))}^2 + \|\varphi_x(0, \cdot)\|_{L^2(0, T)}^2 + (c+1)\|\varphi(0, \cdot)\|_{L^2(0, T)}^2.$$

Proof. Multiplying the equation (3.6) by $(T-t)\varphi$ and integrating by parts over $(0, L) \times (0, T)$, we get

$$\frac{T}{2} \int_0^L \varphi_0^2 dx = \frac{1}{2} \int_0^L \int_0^T \varphi^2 dx dt + \int_0^T \left(\frac{T-t}{2} \right) \left(-(c+1)\varphi^2(L) + (c+1)\varphi^2(0) + \varphi_x^2(0) \right) dt,$$

which yields (3.10) since $c+1 > 0$. $\square$

Equivalently, the following estimate holds for solutions ψ of the system (3.5)

$$(3.11) \quad \|\psi_T\|_{L^2(0,L)}^2 \leq \frac{1}{T} \|\psi\|_{L^2((0,L) \times (0,T))}^2 + (c+1) \|\psi(L, \cdot)\|_{L^2(0,T)}^2 + \|\psi_x(L, \cdot)\|_{L^2(0,T)}^2.$$

Remark 3.5. As a comparison, it is worth pointing out that for the adjoint system of (2.10), which is given by

$$(3.12) \quad \begin{cases} \xi_t + \xi_x + \xi_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ \xi(0, t) = 0, \xi(L, t) = 0, \xi_x(0, t) = 0 & \text{in } (0, T), \\ \xi(x, T) = \xi_T(x) & \text{in } (0, L), \end{cases}$$

the following inequality holds

$$(3.13) \quad \|\xi_T\|_{L^2(0,L)} \leq \frac{1}{T} \|\xi\|_{L^2((0,L) \times (0,T))} + \|\xi_x(L, \cdot)\|_{L^2(0,T)}^2.$$

The extra term $\|\psi(L, \cdot)\|_{L^2(0,T)}^2$ in (3.11) brings a technique difficulty in establishing the observability inequality of the adjoint system (3.5), which calls the use of the hidden regularities established in Proposition 3.2.

Now we turn to analyze the exact controllability of the linear system (3.4).

Proposition 3.6. Assume $c+1 \neq 0$. Let $T > 0$ and $L \notin \mathcal{R}_c$ be given. There exists a bounded linear operator

$$\Psi : L^2(0, L) \times L^2(0, L) \longrightarrow L^2(0, T)$$

such that for any $v_0, v_T \in L^2(0, L)$, if one chooses $h_2 = \Psi(v_0, v_T)$, then system (3.4) admits a solution $v \in \mathcal{Z}_T$ satisfying

$$v|_{t=0} = v_0, \quad v|_{t=T} = v_T.$$

Proof. It suffices to prove that:

For any given $L \in (0, +\infty) \setminus \mathcal{R}_c$ and $T > 0$, there exists a positive constant C depending only on T and L such that

$$(3.14) \quad \|\psi_T\|_{L^2(0,L)} \leq C \|\psi_x(L, t)\|_{L^2(0,T)}$$

holds for any $\psi_T \in L^2(0, L)$, where ψ is the solution of (3.5) with the terminal data ψ_T .

We proceed by contradiction as in [16, Proposition 3.3]. If (3.14) does not hold, then there exists a sequence $\{\psi_T^n\}_{n \in \mathbb{N}} \in L^2(0, L)$ with

$$(3.15) \quad \|\psi_T^n\|_{L^2(0,L)} = 1, \forall n \in \mathbb{N}$$

such that the corresponding solutions of (3.5) satisfy

$$(3.16) \quad 1 = \|\psi_T^n\|_{L^2(0,L)} > n \|\psi_x^n(L, t)\|_{L^2(0,T)},$$

thus $\|\psi_x^n(L, t)\|_{L^2(0,T)} \rightarrow 0$, as $n \rightarrow \infty$. Thanks to Proposition 3.2 we have $\{\psi^n\}_{n \in \mathbb{N}}$ is bounded in $L^2(0, T; H^1(0, L))$ and $\{\psi^n(0, t)\}_{n \in \mathbb{N}}$ is bounded in $H^{\frac{1}{3}}(0, T)$. In addition, according to Proposition 3.4, we have

$$(3.17) \quad \|\psi_T^n\|_{L^2(0,L)} \leq \frac{1}{T} \|\psi^n\|_{L^2((0,L) \times (0,T))}^2 + \|\psi_x^n(L, \cdot)\|_{L^2(0,T)}^2 + (c+1) \|\psi^n(0, \cdot)\|_{L^2(0,T)}^2.$$

Since $\psi_t^n = -(c+1)\psi_x^n - \psi_{xxx}^n$ is bounded in $L^2(0, T; H^{-2}(0, L))$ and the embedding

$$H^1(0, L) \hookrightarrow L^2(0, L) \hookrightarrow H^{-2}(0, L),$$

the sequence $\{\psi^n\}_{n \in \mathbb{N}}$ is relatively compact in $L^2(0, T; L^2(0, L))$ (see [22]). Furthermore, the second term on the right in (3.17) converges to zero in $L^2(0, T)$, and by the compact embedding

$$H^{\frac{1}{3}}(0, T) \hookrightarrow L^2(0, T),$$

the sequence $\{\psi^n(0, t)\}_{n \in \mathbb{N}}$ has a convergent subsequence in $L^2(0, T)$. Therefore by (3.17), $\{\psi_T^n\}_{n \in \mathbb{N}}$ is an $L^2(0, L)$ -Cauchy sequence, thus, at least for a subsequence, we have

$$(3.18) \quad \psi_T^n \longrightarrow \psi_T \text{ in } L^2(0, L),$$

by Theorem 3.2 holds that,

$$(3.19) \quad \psi_x^n(L, t) \longrightarrow \psi_x(L, t) \text{ in } L^2(0, T).$$

From (3.15), (3.18) and (3.19), we have ψ is a solution of

$$(3.20) \quad \begin{cases} \psi_t + (c+1)\psi_x + \psi_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ (c+1)\psi(0, t) + \psi_{xx}(0, t) = 0 & \text{in } (0, T), \\ (c+1)\psi(L, t) + \psi_{xx}(L, t) = 0 & \text{in } (0, T), \\ \psi_x(0, t) = 0 & \text{in } (0, T), \end{cases}$$

satisfying the additional boundary condition

$$(3.21) \quad \psi_x(L, t) = 0$$

and

$$(3.22) \quad \|\psi_T\|_{L^2(0, L)} = 1.$$

Notice that (3.22) implies that the solutions of (3.20)-(3.21) can not be identically zero. Therefore, by the following Lemma 3.7, one can conclude that $\psi \equiv 0$, therefore, $\psi_T(x) \equiv 0$, which contradicts (3.22). $\square$

Lemma 3.7. *For any $T > 0$, let N_T denote the space of the initial states $\psi_T \in L^2(0, L)$ such that the mild solution ψ of (3.20) satisfies (3.21). Then, for $L \in (0, +\infty) \setminus \mathcal{R}_c$, $N_T = \{0\}$, $\forall T > 0$.*

Proof. The proof uses the same arguments as those given in [16]. Therefore, If $N_T \neq \{0\}$, the map $\psi_T \in \mathbb{C}N_T \longrightarrow A(\psi_T) \in \mathbb{C}N_T$ (where $\mathbb{C}N_T$ denote the complexification of N_T) has (at least) one eigenvalue, hence, there exists $\lambda \in \mathbb{C}$ and $\psi_0 \in H^3(0, L) \setminus \{0\}$ such that

$$(3.23) \quad \begin{cases} \lambda\psi_0 = -(c+1)\psi_0' - \psi_0''', \\ (c+1)\psi_0(0) + \psi_0''(0) = 0, \quad (c+1)\psi_0(L) + \psi_0''(L) = 0, \quad \psi_0'(0) = 0, \quad \psi_0'(L) = 0. \end{cases}$$

To conclude the proof of the Lemma 3.7, we prove that this does not hold if $L \notin \mathcal{R}_c$. To simplify the notation, henceforth we denote $\psi_0 := \psi$.

Lemma 3.8. *Let $L > 0$. Consider the assertion*

$$(F) \quad \exists \lambda \in \mathbb{C}, \exists \psi \in H^3(0, L) \setminus \{0\} \text{ such that } \begin{cases} \lambda\psi = -(c+1)\psi' - \psi''', \\ (c+1)\psi(0) + \psi''(0) = 0, \\ (c+1)\psi(L) + \psi''(L) = 0, \\ \psi'(0) = 0, \quad \psi'(L) = 0. \end{cases}$$

Then, (F) holds if and only if $L \in \mathcal{R}_c$.

Proof. We will use the argument developed in [16, Lemma 3.5]. Assume that ψ satisfies $\mathcal{F}$. Let us introduce the notation $\hat{\psi}(\xi) = \int_0^L \psi(x) e^{-ix\xi} dx$. Then, multiplying the equation (3.23) by $e^{-ix\xi}$, integrating by parts in $(0, L)$ and using the boundary condition we obtain

$$(3.24) \quad (\lambda + (c+1)(i\xi) + (i\xi)^3)\hat{\psi}(\xi) = (i\xi)^2\psi(0) - (i\xi)^2\psi(L)e^{-iL\xi}.$$

Setting $\lambda = -ip$, we have

$$(3.25) \quad \hat{\psi}(\xi) = -i\xi^2 \frac{\alpha - \beta e^{-iL\xi}}{\xi^3 - (c+1)\xi + p}$$

with

$$\alpha = \psi(0), \quad \beta = \psi(L).$$

Using Paley-Wiener theorem (see [23, Section 4, page 161]) and the usual characterization of $H^2(\mathbb{R})$ by means of the Fourier transform we see that $\mathcal{F}$ is equivalent to the existence of $p \in \mathbb{C}$ and

$$(\alpha, \beta) \in \mathbb{C}^2 \setminus \{(0, 0)\},$$

such that

$$f(\xi) := \xi^2 \frac{\alpha - \beta e^{-iL\xi}}{\xi^3 - (c+1)\xi + p}$$

satisfies

- a) f is entire function in $\mathbb{C}$;
- b) $\int_{\mathbb{R}} |f(\xi)|^2 (1 + |\xi|^2)^2 d\xi < \infty$;
- c) $\forall \xi \in \mathbb{C}$, we have that $|f(\xi)| \leq c_1 (1 + |\xi|)^k e^{L|\operatorname{Im} \xi|}$ for some positive constants c_1 and k .

Recall that f is a entire function if only if, the roots ξ_0, ξ_1, ξ_2 of $Q(\xi) := \xi^3 - (c+1)\xi + p$ are roots of

$$(3.26) \quad s(\xi) := \xi^2(\alpha - \beta e^{-iL\xi}).$$

In addition, all the roots of $\alpha - \beta e^{-iL\xi}$ are simple, otherwise $\alpha = \beta = 0$ which implies that $\psi(0) = \psi(L) = 0$. Using the system (3.23) we conclude that $\psi \equiv 0$. Besides, as $c+1 \neq 0$, the three roots of $Q(\xi)$ must be simple too.

Let us first assume that $Q(\xi)$ and $\alpha - \beta e^{-iL\xi}$ share the same roots, we can write the three roots of $Q(\xi)$ as

$$(3.27) \quad \xi_1 := \xi_0 + k \frac{2\pi}{L} \quad \text{and} \quad \xi_2 := \xi_1 + l \frac{2\pi}{L}$$

with k and l are some positive integers, we have

$$(3.28) \quad Q(\xi) = (\xi - \xi_0)(\xi - \xi_1)(\xi - \xi_2),$$

that is

$$(3.29) \quad \begin{cases} \xi_0 + \xi_1 + \xi_2 &= 0 \\ \xi_0 \xi_1 + \xi_0 \xi_2 + \xi_1 \xi_2 &= -(c+1) \\ \xi_0 \xi_1 \xi_2 &= -p. \end{cases}$$

Thus we have

$$(3.30) \quad \begin{cases} L &= 2\pi \sqrt{\frac{k^2 + kl + l^2}{3(1+c)}} \\ \xi_0 &= -\frac{1}{3}(2k+l) \frac{2\pi}{L} \\ p &= -\xi_0 \left(\xi_0 + k \frac{2\pi}{L} \right) \left(\xi_0 + (k+l) \frac{2\pi}{L} \right). \end{cases}$$

Next we assume that $\xi = 0$ is a root of $Q(\xi)$, but not of $\alpha - \beta e^{-iL\xi}$. Then three roots of $Q(\xi)$ can be written as $0, \xi_1, \xi_1 + k \frac{2\pi}{L}$ with k being a positive integer. We have

$$(3.31) \quad \begin{cases} \xi_1 + \xi_2 &= 0 \\ \xi_1 \xi_2 &= -(c+1) \\ 0 &= -p, \end{cases}$$

and, consequently, follows that

$$(3.32) \quad \begin{cases} L &= \frac{k\pi}{\sqrt{(1+c)}} \\ \xi_1 &= -k \frac{\pi}{L} \\ p &= 0. \end{cases}$$

Hence, $\mathcal{F}$ holds if and only if $L \in \mathcal{R}_c$. This complete the proof of Lemma 3.8 and, consequently, the proof of Lemma 3.7. $\square$

Finally we consider the case of $c + 1 = 0$. Then it is easy to see that $\xi = 0$ must be a root of $Q(\xi)$; otherwise $L = \infty$. Hence

$$f(\xi) := \frac{\alpha - \beta e^{-iL\xi}}{\xi}.$$

We must have

$$\alpha = \beta \quad \text{or} \quad \psi(0) = \psi(L).$$

(3.23) becomes

$$(3.33) \quad \begin{cases} \psi_0''' = 0, \\ \psi_0''(0) = 0, \quad \psi_0''(L) = 0, \quad \psi_0'(0) = 0, \quad \psi_0'(L) = 0, \quad \psi_0(0) = \psi_0(L) \end{cases}$$

which implies that $\psi_0(x) \equiv C$.

We are now ready to present the proof of Theorem 3.1.

Proof of Theorem 3.1. Rewrite the system (3.2) in its integral form

$$(3.34) \quad v(t) = W_0(t)v_0 + W_{bdr}(t)h - \int_0^t W_0(t - \tau)(vv_x)(\tau, x)d\tau.$$

For any $u \in \mathcal{Z}_T$, let us define

$$\nu(T, u) := \int_0^T W_0(T - \tau)(uu_x)d\tau.$$

By using Proposition 3.6, for any $v_0, v_T \in L^2(0, L)$, if we choose

$$h = \Psi(v_0, v_T + \nu(T, u)),$$

then

$$u(t) = W_0(t)v_0 + W_{bdr}\Psi(v_0, v_t + \nu(T, u)) - \int_0^t W_0(t - \tau)(uu_x)(\tau, x)d\tau$$

satisfies

$$u(x, 0) = v_0(x), \quad u(x, T) = v_T(x) + \nu(T, v) - \nu(T, v) = v_T(x).$$

This leads us to consider the map

$$\Gamma(u) = W_0(t)v_0 + W_{bdr}\Psi(v_0, v_t + \nu(T, u)) - \int_0^t W_0(t - \tau)(uu_x)(\tau, x)d\tau.$$

If we can show that the map Γ is a contraction in an appropriate metric space, then its fixed point u is a solution of (3.2) with $h = \Psi(v_0, v_T + \nu(T, u))$ that satisfies

$$u(x, 0) = v_0(x), \quad u(x, T) = v_T(x).$$

Let

$$B_r = \{z \in \mathcal{Z}_T : \|z\|_{\mathcal{Z}_T} \leq r\}.$$

By Proposition 2.5, there exists a constant $C_1 > 0$ such that for any $u \in \mathcal{Z}_T$,

$$\|\Gamma(u)\|_{\mathcal{Z}_T} \leq C_1 \left(\|v_0\|_{L^2(0, L)} + \|\Psi(v_0, v_t + \nu(T, u))\|_{L^2(0, L)} - \int_0^T \|uu_x\|_{L^2(0, L)}(t)dt \right).$$

Furthermore, as

$$\|\Psi(v_0, v_t + \nu(T, u))\|_{L^2(0, L)} \leq C_2 (\|v_0\|_{L^2(0, L)} + \|v_T\|_{L^2(0, L)} + \|\nu(T, u)\|_{L^2(0, L)})$$

and

$$\|\nu(T, u)\|_{L^2(0, L)} \leq \int_0^T \|uu_x\|_{L^2(0, L)}(t)dt \leq C_3 \|u\|_{\mathcal{Z}_T}^2,$$

we infer that

$$\|\Gamma(u)\|_{\mathcal{Z}_T} \leq C_3 (\|v_0\|_{L^2(0, L)} + \|v_T\|_{L^2(0, L)}) + C_4 \|u\|_{\mathcal{Z}_T}^2,$$

for any $u \in \mathcal{Z}_T$ where C_3 and C_4 are constants depending only T . Thus, if we select r and δ satisfying

$$r = 2C_3\delta$$

and

$$4C_3C_4\delta < \frac{1}{2},$$

then the operator Γ maps B_r into itself for any $v \in B_r$. In addition, for any $\tilde{u}, u \in B_r$, the similar arguments yield that

$$\|\Gamma(u) - \Gamma(\tilde{u})\|_{\mathcal{Z}_T} \leq \gamma \|u - \tilde{u}\|_{\mathcal{Z}_T}$$

with $\gamma = 8C_3C_4\delta < 1$. Therefore the map Γ is a contraction. Its fixed point is a desired solution. The proof of Theorem 3.1 is completed and, consequently, Theorem 1.2 follows. $\square$

4. MULTI CONTROLS AND NULL CONTROLLABILITY

In this section we will first consider the following linear systems associated to (1.12):

$$(4.1) \quad \begin{cases} u_t + u_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = h_1(t), \quad u_x(L, t) = h_2(t), \quad u_{xx}(L, t) = 0 & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L), \end{cases}$$

$$(4.2) \quad \begin{cases} u_t + u_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = 0, \quad u_x(L, t) = h_2(t), \quad u_{xx}(L, t) = h_3(t) & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L) \end{cases}$$

and

$$(4.3) \quad \begin{cases} u_t + u_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = h_1(t), \quad u_x(L, t) = 0, \quad u_{xx}(L, t) = h_3(t) & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L). \end{cases}$$

Proposition 4.1. *Let $T > 0$ and $L > 0$ be given. There exists a bounded linear operator*

$$\Theta : L^2(0, L) \times L^2(0, L) \longrightarrow H^{-\frac{1}{3}}(0, T) \times L^2(0, T)$$

such that for any $u_0, u_T \in L^2(0, L)$, if one chooses

$$(h_1, h_2) = \Psi(u_0, u_T),$$

then system (4.1) admits a solution $u \in \mathcal{Z}_T$ satisfying

$$u(x, 0) = u_0(x), \quad u(x, T) = u_T(x).$$

Proposition 4.2. *Let $T > 0$ and $L > 0$ be given. There exists a bounded linear operator*

$$\Pi : L^2(0, L) \times L^2(0, L) \longrightarrow L^2(0, T) \times H^{-\frac{1}{3}}(0, T)$$

such that for any $u_0, u_T \in L^2(0, L)$, if one chooses

$$(h_2, h_3) = \Psi(u_0, u_T),$$

then system (4.2) admits a solution $u \in \mathcal{Z}_T$ satisfying

$$u(x, 0) = u_0(x), \quad u(x, T) = u_T(x).$$

Proposition 4.3. *Let $T > 0$ and $L > 0$ be given. There exists a bounded linear operator*

$$\Lambda : L^2(0, L) \times L^2(0, L) \longrightarrow H^{-\frac{1}{3}}(0, T) \times H^{-\frac{1}{3}}(0, T)$$

such that for any $u_0, u_T \in L^2(0, L)$, if one chooses

$$(h_1, h_3) = \Psi(u_0, u_T),$$

then system (4.3) admits a solution $u \in \mathcal{Z}_T$ satisfying

$$u(x, 0) = u_0(x), \quad u(x, T) = u_T(x).$$

Propositions 4.1-4.3 follow as a consequence of the following observability inequalities for the solution of the backward system (1.7)

$$(4.4) \quad \|\psi_T\|_{L^2(0,L)} \leq C \left(\|\Delta_t^{\frac{1}{3}} \psi(0, t)\|_{L^2(0,T)} + \|\psi_x(L, t)\|_{L^2(0,T)} \right),$$

$$(4.5) \quad \|\psi_T\|_{L^2(0,L)} \leq C \left(\|\psi_x(L, t)\|_{L^2(0,T)} + \|\Delta_t^{\frac{1}{3}} \psi(L, t)\|_{L^2(0,T)} \right)$$

and

$$(4.6) \quad \|\psi_T\|_{L^2(0,L)} \leq C \left(\|\Delta_t^{\frac{1}{3}} \psi(0, t)\|_{L^2(0,T)} + \|\Delta_t^{\frac{1}{3}} \psi(L, t)\|_{L^2(0,T)} \right),$$

where $\Delta_t := (I - \partial_t^2)^{\frac{1}{2}}$. The proofs of (4.4)-(4.6) are similar to that of (3.14). Furthermore, Theorem 1.6 can be proved using the same arguments as that in the proof of Theorem 3.1, their proof is thus omitted.

Concerning the null controllability, that is, the proof of Theorem 1.9, note that for the linear system we can get the result using the Carleman estimate provided by [11, Proposition 3] together with the following remark:

Remark 4.4. *The following systems*

$$(4.7) \quad \begin{cases} u_t + u_x + u_{xxx} = f & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = h_1(t), \quad u_x(L, t) = 0, \quad u_{xx}(L, t) = 0 & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L) \end{cases}$$

and

$$(4.8) \quad \begin{cases} y_t + y_x + y_{xxx} = f & \text{in } (0, L) \times (0, T), \\ y(0, t) = k_1(t), \quad y_x(L, t) = 0, \quad y_{xx}(L, t) = 0 & \text{in } (0, T), \\ y(x, 0) = y_0(x) & \text{in } (0, L) \end{cases}$$

are equivalent in the following sense:

For given $\{u_0, f, h_1\}$ one can find $\{y_0, f, k_1\}$ such that the corresponding solution u of (4.7) is exactly the same as the corresponding solution y for the system (4.8) and vice versa.

Indeed, for given $u_0 \in L^2(0, L)$, $f \in L^1(0, T; L^2(0, L))$ and $h_1(t) \in H^{-\frac{1}{3}}(0, T)$, system (4.7) admits a unique solution $u \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$. Let $y_0 = u_0$ and set $k_1(t) = h_1(t)$. Then, according to Proposition 2.6, we have $k_1(t) \in H^{\frac{1}{3}}(0, T)$. Due to the uniqueness of IBVP (4.8), with the selection $\{y_0, f, k_1\}$, the corresponding solution $y \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$ of (4.8) must be equal to u , since u also solves (4.8) with the given auxiliary data $\{y_0, f, k_1\}$. On the other hand, for any given $y_0 \in L^2(0, L)$, $f \in L^1(0, T; L^2(0, L))$ and $k_1(t) \in H^{\frac{1}{3}}(0, T)$, let $y \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$ be the corresponding solution of the system (4.8). From Proposition 2.6, we have $y_{xx}(0, \cdot) \in H^{-\frac{1}{3}}(0, T)$. Thus, if $u_0 = y_0$ and $h_1(t) = k_1(t)$, then $h_1(t) \in H^{-\frac{1}{3}}(0, T)$ and the corresponding solution $u \in C([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L))$ of (4.7) must be equal to y , which also solves (4.7) with the auxiliary data $\{u_0, f, h_1\}$.

Proof of Theorem 1.9: Consider u and $\bar{u}$ fulfilling system (1.13) and (1.14), respectively. Then $q = u - \bar{u}$ satisfies

$$(4.9) \quad \begin{cases} q_t + q_x + (\frac{q^2}{2} + \bar{u}q)_x + q_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ q_{xx}(0, t) = \bar{h}_1(t), \quad q_x(L, t) = 0, \quad q_{xx}(L, t) = 0 & \text{in } (0, T), \\ q(x, 0) = q_0(x) := u_0(x) - \bar{u}_0(x) & \text{in } (0, L). \end{cases}$$

The objective is to find $\bar{h}_1$ such that the solution q of (4.9) satisfies

$$q(\cdot, T) = 0.$$

Given $\xi \in \mathcal{Z}_T$ and $q_0 := u_0 - \bar{u}_0 \in L^2(0, L)$, we consider the following control problem

$$(4.10) \quad q_t + q_x + (\xi q)_x + q_{xxx} = 1_\omega v(t, x) \quad \text{in } (0, L) \times (0, T),$$

$$(4.11) \quad q_{xx}(0, t) = q_x(L, t) = q_{xx}(L, t) = 0 \quad \text{in } (0, T),$$

$$(4.12) \quad q(x, 0) = q_0(x) \quad \text{in } (0, L),$$

where v is solution of the following adjoint system

$$(4.13) \quad \begin{cases} v_t + \xi(t, x)v_x + v_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ v(0, t) + v_{xx}(0, t) = 0 & \text{in } (0, T), \\ v(L, t) + v_{xx}(L, t) = 0 & \text{in } (0, T), \\ v_x(L, t) = 0, & \text{in } (0, T), \\ v(x, 0) = v_0(x), & \text{in } (0, L). \end{cases}$$

We can prove the following estimate

$$(4.14) \quad \|q\|_{L^\infty(0, T, L^2(0, L))}^2 + 2\|q_x\|_{L^2(0, T, L^2(0, L))}^2 \leq \tilde{C}(T, L, \|\xi\|_{\mathcal{Z}_T})(\|q_0\|_{L^2(0, L)}^2 + \|v\|_{L^2((0, T) \times \omega)}^2).$$

We introduce the space

$$E := C^0([0, T]; L^2(0, L)) \cap L^2(0, T; H^1(0, L)) \cap H^1(0, T; H^{-2}(0, L)),$$

and in $L^2((0, T) \times (0, L))$ the following set

$$B := \{z \in E; \|z\|_E \leq 1\}.$$

B is compact in $L^2((0, T) \times (0, L))$, by Aubin-Lions's lemma. We will limit ourselves v fulfilling the condition

$$(4.15) \quad \|v\|_{L^2((0, T) \times \omega)}^2 \leq C_* \|q_0\|_{L^2(0, L)}^2,$$

where $C_* := C_*(T, L, \|\bar{u}\|_{\mathcal{Z}_T} + \frac{1}{2})$. We associate with any $z \in B$, solutions of the linear system (4.7), the set

$$T(z) := \left\{ q \in B; \exists v \in L^2((0, T) \times \omega) \text{ such that } v \text{ satisfies (4.15) and } q \text{ solves (4.10)-(4.12) with } \xi = \bar{u} + \frac{z}{2} \text{ and } q(\cdot, T) = 0 \right\}.$$

By the result of the linear system (see [11, Theorem 1]) and (4.14), we see that if $\|q_0\|_{L^2(0, L)}$ and T are sufficiently small, then $T(z)$ is nonempty for all $z \in B$. We shall use the following version of Kakutani fixed point theorem (see e.g. [24, Theorem 9.B]):

Theorem 4.5. *Let F be a locally convex space, let $B \subset F$ and let $T : B \rightarrow 2^B$. Assume that*

- (1) *B is a nonempty, compact, convex set;*
- (2) *$T(z)$ is a nonempty, closed, convex set for all $z \in B$;*
- (3) *The set-valued map $T : B \rightarrow 2^B$ is upper-semicontinuous; i.e., for every closed subset A of F , $T^{-1}(A) = \{z \in B; T(z) \cap A \neq \emptyset\}$ is closed.*

Then T has a fixed point, i.e., there exists $z \in B$ such that $z \in T(z)$.

Let us check that Theorem 4.5 can be applied to T and

$$F = L^2((0, T) \times (0, L)).$$

The convexity of B and $T(z)$ for all $z \in B$ is clear. Thus (1) is satisfied. For (2), it remains to check that $T(z)$ is closed in F for all $z \in B$. Pick any $z \in B$ and a sequence $\{q^k\}_{k \in \mathbb{N}}$ in $T(z)$ which converges in F towards some function $q \in B$. For each k , we can pick some control function $v^k \in L^2((0, T) \times \omega)$ fulfilling (4.15) such that (4.10)-(4.12) are satisfied with $\xi = \bar{u} + \frac{z}{2}$ and $q^k(\cdot, T) = 0$. Extracting subsequences if needed, we may assume that as $k \rightarrow \infty$

$$(4.16) \quad v^k \rightarrow v \quad \text{in } L^2((0, T) \times \omega) \text{ weakly,}$$

$$(4.17) \quad q^k \rightarrow q \quad \text{in } L^2(0, T; H^1(0, L)) \cap H^1(0, T; H^{-2}(0, L)) \text{ weakly.}$$

By (4.17), the boundedness of $\|q^k\|_{L^\infty(0,T,L^2(0,L))}$ and Aubin-Lions' lemma, $\{q^k\}_{k \in \mathbb{N}}$ is relatively compact in $C^0([0,T], H^{-1}(0,L))$. Extracting a subsequence if needed, we may assume that

$$q^k \rightarrow q \text{ strongly in } C^0([0,T], H^{-1}(0,L)).$$

In particular, $q(x,0) = q_0(x)$ and $q(x,T) = 0$. On the other hand, we infer from (4.17) that

$$\xi q^k \rightarrow \xi q \text{ in } L^2((0,T) \times (0,L)) \text{ weakly.}$$

Therefore, $(\xi q^k)_x \rightarrow (\xi q)_x$ in $\mathcal{D}'((0,T) \times (0,L))$. Finally, it is clear that

$$\|v\|_{L^2((0,T) \times \omega)}^2 \leq C_* \|q_0\|_{L^2(0,L)}^2$$

and that q satisfies (4.10) with $\xi = \bar{u} + \frac{z}{2}$ and $q(\cdot, T) = 0$. Thus $q \in T(z)$ and $T(z)$ is closed. Now, let us check (3). To prove that T is upper-semicontinuous, consider any closed subset A of F and any sequence $\{z^k\}_{k \in \mathbb{N}}$ in B such that

$$(4.18) \quad z^k \in T^{-1}(A), \quad \forall k \geq 0$$

and

$$(4.19) \quad z^k \rightarrow z \text{ in } F,$$

for some $z \in B$. We aim to prove that $z \in T^{-1}(A)$. By (4.18), we can pick a sequence $\{q^k\}_{k \in \mathbb{N}}$ in B with $q^k \in T(z^k) \cap A$ for all k , and a sequence $\{v^k\}_{k \in \mathbb{N}}$ in $L^2((0,T) \times \omega)$ such that

$$(4.20) \quad \begin{cases} q_t^k + q_x^k + ((\bar{u} + \frac{z^k}{2})q^k)_x + q_{xxx}^k = 1_\omega v^k(t, x) & \text{in } (0,L) \times (0,T), \\ q_{xx}^k(0,t) = q_x^k(L,t) = q_{xx}^k(L,t) = 0 & \text{in } (0,T), \\ q^k(x,0) = q_0(x) & \text{in } (0,L), \end{cases}$$

$$(4.21) \quad q^k(x,T) = 0, \quad \text{in } (0,L)$$

and

$$(4.22) \quad \|v^k\|_{L^2((0,T) \times \omega)}^2 \leq C_* \|q_0\|_{L^2(0,L)}^2.$$

From (4.22) and the fact that $z^k, q^k \in B$, extracting subsequences if needed, we may assume that as $k \rightarrow \infty$,

$$\begin{aligned} v^k &\rightarrow v && \text{in } L^2((0,T) \times \omega) \text{ weakly,} \\ q^k &\rightarrow q && \text{in } L^2(0,T; H^1(0,L)) \cap H^1(0,T; H^{-2}(0,L)) \text{ weakly,} \\ q^k &\rightarrow q && \text{in } C^0([0,T], H^{-1}(0,L)) \text{ strongly,} \\ q^k &\rightarrow q && \text{in } F \text{ strongly,} \\ z^k &\rightarrow z && \text{in } F \text{ strongly,} \end{aligned}$$

where $v \in L^2((0,T) \times \omega)$ and $q \in B$. Again, $q(x,0) = q_0(x)$ and $q(x,T) = 0$. We also see that (4.11) and (4.15) are satisfied. It remains to check that

$$(4.23) \quad q_t + q_x + ((\bar{u} + \frac{z}{2})q)_x + q_{xxx} = 1_\omega v(t, x).$$

Observe that the only nontrivial convergence in (4.20) is those of the nonlinear term $(z^k q^k)_x$. Note first that

$$\|z^k q^k\|_{L^2(0,T,L^2(0,L))} \leq \|z^k\|_{L^\infty(0,T,L^2(0,L))} \|q^k\|_{L^2(0,T,L^\infty(0,L))} \leq C,$$

so that, extracting a subsequence, one can assume that $z^k q^k \rightarrow f$ weakly in $L^2((0,T) \times (0,L))$. To prove that $f = zq$, it is sufficient to observe that for any $\varphi \in \mathcal{D}(Q)$,

$$\int_0^T \int_0^L z^k q^k \varphi dx dt \rightarrow \int_0^T \int_0^L z q \varphi dx dt,$$

for $z^k \rightarrow z$ and $q^k \varphi \rightarrow q \varphi$ in F . Thus

$$z^k q^k \rightarrow zq \quad \text{in } L^2((0,T) \times (0,L)) \text{ weakly.}$$

It follows that $(z^k q^k)_x \rightarrow (zq)_x$ in $\mathcal{D}'((0, T) \times (0, L))$. Therefore, (4.23) holds and $q \in T(z)$. On the other hand, $q \in A$, since $q^k \rightarrow q$ in F and A is closed. We conclude that $z \in T^{-1}(A)$, and hence $T^{-1}(A)$ is closed.

Thus, follows from Theorem 4.5 that there exists $q \in B$ with $q \in T(q)$, i.e. we have found a control $h_1 \in L^2(0, T)$ such that the solution of (4.9) satisfies $q(\cdot, T) = 0$ in $(0, L)$. The proof of Theorem 1.9 is finished. $\square$

Finally we consider the boundary control system

$$(4.24) \quad \begin{cases} u_t + u_x + uu_x + u_{xxx} = 0 & \text{in } (0, L) \times (0, T), \\ u_{xx}(0, t) = h_1(t), \quad u_x(L, t) = h_2(t), \quad u_{xx}(L, t) = h_3(t) & \text{in } (0, T), \\ u(x, 0) = u_0(x) & \text{in } (0, L), \end{cases}$$

with all three control inputs being used and present the proofs of Theorem 1.7 and Theorem 1.8.

Proof of Theorem 1.7: Consider the the initial value control of the KdV equation posed the the whole line $\mathbb{R}$:

$$(4.25) \quad w_t + w_x + ww_x + w_{xxx} = 0, \quad w(x, 0) = g(x) \quad x \in \mathbb{R}, \quad t \in (0, T),$$

where the initial value g is considered as a control input. By [25, Theorem 1.2] there exists a $\delta > 0$ such that, for $s \geq 0$, if $u_0, u_T \in H^s(0, L)$ satisfying

$$\|u_0(\cdot) - y(\cdot, 0)\|_{H^s(0, L)} + \|u_T(\cdot) - y(\cdot, T)\|_{H^s(0, L)} \leq \delta,$$

then one can choose $g \in H^s(\mathbb{R})$ so that (4.25) admits a solution

$$w \in C([0, T]; H^s(\mathbb{R}) \cap L^2(0, T; H^{s+1}(\mathbb{R})))$$

with

$$w(x, 0) = u_0(x), \quad w(x, T) = u_T(x) \quad \text{for } x \in (0, L).$$

Moreover, the solution w possesses the sharp Kato smoothing properties with

$$h_1(t) := w_{xx}(0, t) \in H^{\frac{s-1}{3}}(0, T), \quad h_2(t) := w_x(L, t) \in H^{\frac{s}{3}}(0, T), \quad h_3 := w_{xx}(L, t) \in H^{\frac{s-1}{3}}(0, T).$$

Thus with such chosen control inputs $h_j, j = 1, 2, 3$,

$$u(x, t) := w(x, t), \quad \text{for } x \in (0, L), \quad t \in (0, T)$$

solves system (4.24) and satisfies

$$u(x, 0) = u_0(x), \quad u(x, T) = u_T(x), \quad \text{for } x \in (0, L).$$

We have, thus, completed the proof of Theorem 1.7. $\square$

Proof of Theorem 1.8: Without loss of generality, we assume $u_T = 0$. Consider feedback control system of the KdV equation posed on the interval $(-L, L)$:

$$(4.26) \quad \begin{cases} v_t + v_x + vv_x + v_{xxx} + b(x)v = 0 & v(x, 0) = \tilde{u}_0(x) & x \in (-L, L), \quad t \in (0, T), \\ v(-L, t) = 0, \quad v(L, t) = 0, \quad v_x(L, t) = 0 & & t \in (0, T), \end{cases}$$

where

$$b(x) = \begin{cases} 1 & x \in (-\frac{4}{3}L, -\frac{1}{2}L), \\ 0 & \text{otherwise} \end{cases}$$

and

$$\tilde{u}_0(x) = \begin{cases} u_0(x) & x \in (0, L), \\ 0 & \text{otherwise.} \end{cases}$$

It follows from [25] that, for given $u_0 \in L^2(0, L)$, we have

$$v \in C_b(\mathbb{R}^+, L^2(-L, L)) \cap L^2_{loc}(\mathbb{R}^+; H^1(-L, L))$$

and, there exists a $\nu > 0$ such that

$$\|v(\cdot, t)\|_{L^2(-L, L)} \leq C \|u_0\|_{L^2(0, L)} e^{-\nu t}, \quad \text{for any } t \geq 0.$$

For given $\delta > 0$, choose t^* large enough such that

$$\|v(\cdot, t^*)\|_{L^2(-L, L)} \leq C\|u_0\|_{L^2(0, L)}e^{-\nu t^*} \leq \delta.$$

Then, again by [25, Theorem 1.2], one can find a control $h \in L^2(t^*, t^* + 1)$ such that (1.1) admits a solution $z \in C([t^*, t^* + 1]; L^2(0, L) \cap L^2(t^*, t^* + 1; H^1(0, L)))$ satisfying

$$z(x, t^*) = v(x, t^*), \quad z(x, t^* + 1) = 0 \quad x \in (0, L).$$

Let $T = t^* + 1$,

$$h_1(t) := \begin{cases} v_{xx}(0, t) & t \in (0, t^*), \\ 0 & t \in (t^*, T), \end{cases} \quad h_2(t) := \begin{cases} v_x(L, t) & t \in (0, t^*), \\ h(t) & t \in (t^*, T) \end{cases}$$

and

$$h_3(t) := \begin{cases} v_{xx}(L, t) & t \in (0, t^*), \\ 0 & t \in (t^*, T). \end{cases}$$

Note that as the solutions of (4.26) possess the sharp Kato smoothing properties we have

$$h_1 \in H^{-\frac{1}{3}}(0, T), \quad h_2 \in L^2(0, T), \quad h_3 \in H^{-\frac{1}{3}}(0, T).$$

Thus if we let

$$u(x, t) := \begin{cases} v(x, t) & x \in (0, L), \quad t \in (0, t^*), \\ z(x, t) & x \in (0, L), \quad t \in (t^*, T), \end{cases}$$

then $u \in C([0, T]; L^2(0, L) \cap L^2(0, T; H^1(0, L)))$ solves (4.24) and satisfies

$$u(x, 0) = u_0(x), \quad u(x, T) = 0, \quad \text{for } x \in (0, L).$$

Thus, the proof of Theorem 1.8 is achieved. $\square$

Acknowledgments:

Roberto A. Capistrano-Filho was supported by CNPq (Brazilian Technology Ministry), Project PDE, grant 229204/2013-9 and partially supported by CAPES (Brazilian Education Ministry). Bing-Yu Zhang was supported by a grant from the Simons Foundation (201615), NSF of China (11231007) and PCSIRT (Chinese Education Ministry) under grant IRT 1273.

REFERENCES

- [1] J. J. Bona, S. M. Sun and Zhang, B.-Y., *A nonhomogeneous boundary-value problem for the Korteweg-de Vries equation posed on a finite domain*, Comm. Partial Differential Equations, 28 (2003), pp.1391–1438.
- [2] J. Bourgain, *Fourier transform restriction phenomena for certain lattice subsets and applications to nonlinear evolution equations, part I: Schrödinger equations*, Geom. Funct. Anal., 3 (1993), pp. 107–156.
- [3] J. Bourgain, *Fourier transform restriction phenomena for certain lattice subsets and applications to nonlinear evolution equations, part II: the KdV-equation*, Geom. Funct. Anal., 3 (1993), 209–262.
- [4] E. Cerpa, *Exact controllability of a nonlinear Korteweg-de Vries equation on a critical spatial domain*, SIAM J. Control Optim., 46 (2007), pp. 877–899.
- [5] E. Cerpa, *Control of a Korteweg-de Vries equation: a tutorial*, Math. Control Relat. Fields, 4 (2014), pp. 45–99.
- [6] E. Cerpa and E. Crépeau, *Boundary controllability for the nonlinear Korteweg-de Vries equation on any critical domain*, Ann. I.H. Poincaré, 26 (2009), pp. 457–475.
- [7] J.-M. Coron, *Local controllability of a 1-D tank containing a fluid modeled by the shallow water equations*, ESAIM Control Optim. Calc. Var., 8 (2002), pp. 513–554.
- [8] J.-M. Coron and E. Crépeau, *Exact boundary controllability of a nonlinear KdV equation with a critical length*, J. Eur. Math. Soc., 6 (2004), pp. 367–398.
- [9] O. Glass and S. Guerrero, *Some exact controllability results for the linear KdV equation and uniform controllability in the zero-dispersion limit*, Asymptot. Anal., 60 (2008), pp. 61–100.
- [10] O. Glass and S. Guerrero, *Controllability of the Korteweg-de Vries equation from the right Dirichlet boundary condition*, Systems Control Lett., 59 (2010), pp. 390–395.
- [11] J.-P. Guilleron, *Null controllability of a linear KdV equation on an interval with special boundary conditions*, Math. Control Signals Syst., 26 (2014), pp. 375–401.
- [12] C. E. Kenig, G. Ponce and L. Vega, *Well-posedness of the initial value problem for the Korteweg-de Vries equation*, J. Amer. Math. Soc., 4 (1991), pp. 323–347.
- [13] E. Kramer and B.-Y. Zhang, *Nonhomogeneous boundary value problems for the Korteweg-de Vries equation on a bounded domain*, J. Syst. Sci. Complex, 23 (2010), pp. 499–526.

- [14] E. Kramer, I. Rivas and B.-Y. Zhang, *Well-posedness of a class of initial-boundary-value problem for the Korteweg-de Vries equation on a bounded domains*, ESAIM Control Optim. Calc. Var., 19 (2013), pp. 358–384.
- [15] C. Laurent, L. Rosier and B.-Y. Zhang, *Control and Stabilization of the Korteweg-de Vries Equation on a Periodic Domain*, Comm. Partial Differential Equations, 35 (2010), pp. 707–744.
- [16] L. Rosier, *Exact boundary controllability for the Korteweg-de Vries equation on a bounded domain*, ESAIM Control Optim. Cal. Var., 2 (1997), pp. 33–55.
- [17] L. Rosier, *Control of the surface of a fluid by a wavemaker*, ESAIM Control Optim. Cal. Var., 10 (2004), pp. 346–380.
- [18] L. Rosier and B.-Y. Zhang, *Control and stabilization of the Korteweg-de Vries equation: Recent progresses*, J. Syst Sci & Complexity, 22 (2009), pp. 647–682.
- [19] D. L. Russell, *Computational study of the Korteweg-de Vries equation with localized control action*, Distributed Parameter Control Systems: New Trends and Applications, G. Chen, E. B. Lee, W. Littman, and L. Markus, eds., Marcel Dekker, New York, 1991.
- [20] D. L. Russell and B.-Y. Zhang, *Controllability and stabilizability of the third- order linear dispersion equation on a periodic domain*, SIAM J. Control and Optimization, 31 (1993), pp. 659 – 676.
- [21] D. L. Russell and B.-Y. Zhang, *Exact controllability and stabilizability of the Korteweg-de Vries equation*, Trans. Amer. Math. Soc., 348 (1996), pp. 3643–3672.
- [22] J. Simon, *Compact sets in the $L^p(0; T; B)$ spaces*, Analli Mat. Pura Appl., 146 (1987), pp. 65–96.
- [23] K. Yosida, *Functional Analysis*, Springer-Verlag, Berlin Heidelberg New York ,1978.
- [24] E. Zeidler, *Nonlinear functional analysis and its applications I*, Springer-Verlag, New York, 1986.
- [25] B.-Y. Zhang, *Exact boundary controllability of the Korteweg-de Vries equation*, SIAM J. Cont. Optim., 37 (1999), pp. 543–565.
- [26] B.-Y. Zhang, *Some results for nonlinear dispersive wave equations with applications to control*, Ph. D thesis, University of Wisconsin-Madison, 1990.

DEPARTMENT OF MATHEMATICAL SCIENCES, UNIVERSITY OF CINCINNATI, 2815 COMMONS WAY -FRENCH HALL WEST CINCINNATI, OHIO - 45221 UNITED STATES
E-mail address: caicedms@mail.uc.edu

DEPARTMENT OF MATHEMATICAL SCIENCES, UNIVERSITY OF CINCINNATI, 2815 COMMONS WAY -FRENCH HALL WEST CINCINNATI, OHIO - 45221 UNITED STATES
E-mail address: capistranofilho@gmail.com

DEPARTMENT OF MATHEMATICAL SCIENCES, UNIVERSITY OF CINCINNATI, CINCINNATI , OHIO 45221-0025
 AND YANGTZE CENTER OF MATHEMATICS, SICHUAN UNIVERSITY, CHENGDU, CHINA
E-mail address: zhangb@ucmail.uc.edu